

Tunnelling of polarized electrons in magnetic wires

D. Schmeltzer

Physics Department

City College of the City University of New York

New York, New York 10031

(Dated: March 1, 2009)

Abstract

We investigate the tunnelling between an electronic gas with two different velocities $V_{\uparrow} \neq V_{\downarrow}$ and a regular metal. We find that at the interface between the two systems that the tunnelling conductance for spin up and spin down are different. As a result a partly polarized gas (“magnetic wire”) is obtained. This result is caused by the e-e interaction, $g_2'' - g_1'' \neq 0$, which in the presence of $V_{\uparrow} \neq V_{\downarrow}$ gives rise to two different tunnelling exponents.

PACS numbers:

Following ideas of transport in “Quantum Wires” we can study transport and tunnelling of polarized electrons. Studies of polarized electrons in the diffusive regime have been considered by Aronov [1]. Recently the spin analog of the bipolar p-n-p transistor and F.E.T. have been suggested [2-4]. These studies have inspired us to study tunnelling in the “Quantum Wire” regime between a ferromagnetic wire and a metallic one. The analog of the p-n-p transistor can be simulated with the help of magnetic wires using two ferromagnetic metallic (FM) wires coupled to a metallic (M) dot. We obtain a double junction FM-M-FM. When the ferromagnetic wires have parallel polarization, we obtain a low resistance device which is switched off when the two wires are antiparallel polarized.

As a first step in this direction we will investigate the tunnelling between a quantum wire in the presence of interaction with two different Fermi velocities (for spin up and spin down) to a metallic wire. The origin of the two Fermi velocities is the presence of an external magnetic field and/or the presence of Ferromagnetic interactions. As a result, we have a situation where the two channels (spin up and spin down) have two different velocities, $V_\uparrow$, $V_\downarrow$. In one dimension the ballistic conductance is independent from the velocity. Therefore in the absence of electron electron interaction the ballistic conductance for spin up and down are equal $G_\uparrow = G_\downarrow = e^2/h$ despite of the fact that the two Fermi velocities are different, $V_\uparrow \neq V_\downarrow$. In order to obtain $G_\uparrow \neq G_\downarrow$ we have to take in consideration the electron-electron interaction. The electron-electron interaction in one dimension causes fractionalization of the electron. This is observed in tunnelling experiments where the interaction gives rise to an orthogonality catastrophe controlled by $K = V_F/V_P$ (“ V_F ” is the Fermi velocity and “ V_P ” is the velocity of the collective excitations)[5]. For a polarized gas $V_\uparrow > V_\downarrow$ one has two interaction parameters $K_\uparrow = V_\uparrow/V_P$, $K_\downarrow = V_\downarrow/V_P$. Due to the fact that $V_\uparrow > V_\downarrow$ we obtain $1 > K_\uparrow > K_\downarrow$. As a result the tunnelling for the two channels will be different. The tunnelling conductance between a polarized gas with interaction and a metallic one is suggested to be: $G_\uparrow \simeq \frac{e^2}{h}|t|^2\ell^{2(\frac{1}{K_\uparrow}-1)}$, $G_\downarrow \simeq \frac{e^2}{h}|t|^2\ell^{2(\frac{1}{K_\downarrow}-1)}$ where “ t ” is the tunnelling matrix between the magnet wire and the metallic one and $\ell = \frac{1}{a} \min[L, L_T]$, “ a ” is the lattice spacing, L is the length of the wire and $L_T = \frac{\hbar V_F}{k_B T}$ is the thermal length. In the limit of long wires $L > L_T$, the tunnelling is controlled by the temperature and one can replace “ ℓ ” with $\frac{T_F}{T}$. $\tilde{T}_F$ is the thermal ultraviolet cutoff, $\tilde{T}_F = \frac{\hbar V}{K_B a}$, replacing $1/a$ with the Fermi momentum K_F and the velocity V with V_F we obtain the Fermi temperature, $T_F = \frac{\hbar V_F K_F}{K_B}$. (In our problem we have two pairs of Fermi velocities, $V_\uparrow$, V_F and $V_\downarrow$, V_F , the use of Fermi

temperature T_F as a U.V. cutoff is an approximation). The polarization degree will be controlled by the difference $\frac{1}{K_\uparrow} - \frac{1}{K_\downarrow}$. Therefore, increasing the difference $V_\uparrow - V_\downarrow$, lowering the temperature and increasing the electron-electron interaction will enhance the anisotropy of the conductance $\frac{G_\perp}{G_\uparrow} = (\frac{T}{T_F})^{2\frac{K_\uparrow - K_\downarrow}{K_\uparrow K_\downarrow}}$. Since $K_\uparrow < K_\downarrow$, we obtain at low temperature a strong polarization, $\frac{G_\perp}{G_\uparrow} \rightarrow 0$. When $T \rightarrow 0$ the value of the conductance is controlled by the length of the wire “L” since $L < L_T$, we obtain $\frac{G_\perp}{G_\uparrow} = (\frac{a}{L})^{2\frac{K_\uparrow - K_\downarrow}{K_\uparrow K_\downarrow}}$.

We find that the interaction parameter $g_2'' - g_1''$ (the difference between the forward and backward interaction) controls the polarization. In particular when $g_1 < 0$ (attractive interaction with large momentum transfer), the polarization is enhanced.

Next we present the model and the calculation. The hamiltonian it is given by $H^{(1)} + H^{(2)} + H_T$. $H^{(1)}$ represents a polarized channel with electron-electron interaction. $H^{(2)}$ is a metallic wire and H_T is the tunnelling part between the two wires.

The first wire is restricted to the region $-L \leq x \leq 0$. $H_0^{(1)}$ is the kinetic energy with two velocities $V_\uparrow, V_\downarrow, V_\uparrow - V_\downarrow = \Delta$. $H_I^{(1)}$ is the e-e interaction away from half-filling,

$$H_I^{(1)} = \int_{-L}^0 dx \sum_{\sigma, \sigma'} \{ g_1 R_\sigma^+(x) L_{\sigma'}^+(x) R_{\sigma'}(x) L_\sigma(x) + g_2 R_\sigma^+(x) L_{\sigma'}^+(x) L_{\sigma'}(x) R_\sigma(x) + g_4 (1 - \delta_{\sigma, \sigma'}) [R_\sigma^+(x) R_{\sigma'}^+(x) R_{\sigma'}(x) R_\sigma(x) + R \leftrightarrow L] \} \quad (1)$$

The form of the interaction hamiltonian given in eq.(1) has been obtained with the help of the fermion operators $\tilde{\psi}_\sigma(x), \tilde{\psi}_\sigma^+(x)$, $\sigma = \uparrow, \downarrow$ in terms of the right and left movers, $\tilde{\psi}_\sigma(x) = e^{iK_F x} R_\sigma(x) + e^{-iK_F x} L_\sigma(x)$. $g_1 = g_1^\perp(0) = g_1''(0)$ denotes the backward $(K_F, -K_F) \rightarrow (-K_F, K_F)$ and $g_2 = g_2^\perp(0) = g_2''(0)$ denote the forward $(-K_F, K_F) \rightarrow (-K_F, K_F)$ scattering potentials.

The backward interaction can be split into g'' and $g_1^\perp$, g_1'' controls the spin and charge density interaction. This notation emphasizes the connection with the Kondo parameters - $J_\parallel$ and $J_\perp$.

We will bosonize the hamiltonian $H^{(1)}$ using open boundary conditions, $\tilde{\psi}_\sigma(0) = \tilde{\psi}_\sigma(-L) = 0$. We will follow reference [6] and we will introduce a chiral fermion $\psi_\sigma(x)$ which will obey periodic boundary condition and can be bosonized according to the stan-

standard rules.

$$\psi_\sigma(x) = \begin{cases} R_\sigma(x) & x > 0 \\ L_\sigma(-x) & x < 0 \end{cases}, \quad R_\sigma(x) = -L_\sigma(-x) \quad (2a)$$

$$\psi_\sigma(x) = \frac{1}{\sqrt{2\pi d}} \exp[i\sqrt{4\pi}\theta_\sigma(x)] \quad (2b)$$

$$J_\sigma(x) =: \psi_\sigma^+(x)\psi_\sigma(-x) := \frac{1}{\sqrt{\pi}}\partial_x\theta_\sigma(x) \quad (2c)$$

$$J_\sigma(x) = \begin{cases} : R_\sigma^+(x)R_\sigma(x) : & x > 0 \\ : L_\sigma^+(x)L_\sigma(-x) : & x < 0 \end{cases} \quad (2d)$$

$J_\sigma(x)$ and $\theta_\sigma(x)$ are the chiral current and chiral bosonic field. Using the chiral boson representation we obtain the bosonic representation for the region $-L < x \leq 0$.

$$H^{(1)} = H_0^{(1)} + H_I^{(1)}$$

$$H_0^{(1)} = \int_{-L}^L dx \{ \pi V_\uparrow J_\uparrow^2(x) + \pi V_\downarrow J_\downarrow^2(x) \}, \quad V_\uparrow - V_\downarrow = \Delta \quad (3a)$$

$$\begin{aligned} H_I^{(1)} = & \int_{-L}^L dx \left\{ \frac{1}{2}(g_2^\parallel - g_1^\parallel)(J_\uparrow(x)J_\uparrow(-x) + J_\downarrow(x)J_\downarrow(-x)) \right. \\ & + \frac{1}{2}g_2^\perp(J_\uparrow(x)J_\downarrow(-x) + J_\downarrow(x)J_\uparrow(-x)) + g_4J_\uparrow(x)J_\downarrow(x) \\ & \left. + \frac{g_1^\perp}{2(\pi d)^2} \cos[\sqrt{4\pi}(\theta_\uparrow(x) + \theta_\uparrow(-x) - \theta_\downarrow(x) - \theta_\downarrow(-x)) + 2K_F \left(\frac{\Delta}{2V_F} \right) x] \right\} \quad (3b) \end{aligned}$$

From eq.3b we observe that the Luttinger parameter which controls separately the spin up and spin down excitations is given by $g_2'' - g_1''$. The difference in the velocities $V_\uparrow - V_\downarrow = \Delta$ represents the Zeeman energy and $\frac{V_\uparrow + V_\downarrow}{2} = V_F$ is the Fermi velocity. The last term in eq. 3b will be ignored here since it contains the oscillating term $2K_F(\frac{\Delta}{2V_F})x$.

We will investigate the case with the Zeeman term $\Delta \neq 0$ and therefore we will neglect the cosine term. We will diagonalize the hamiltonian in eqs. 3a - 3b performing a set of transformations which leaves the commutation rules invariant.

We introduce two new chiral currents $J_+(x)$ and $J_-(x)$

$$J_\uparrow(x) = aJ_+(x) + bJ_-(x)$$

$$J_\downarrow(x) = bJ_+(x) - aJ_-(x)$$

where $a^2 + b^2 = 1$, and a second transformation for the new variables $\tilde{J}_+(x), \tilde{J}_-(x)$.

$$J_\pm(x) = \frac{K_\pm^{1/2}}{2}(\tilde{J}_\pm(x) + \tilde{J}_\pm(-x)) + \frac{K_\pm^{-1/2}}{2}(\tilde{J}_\pm(x) - \tilde{J}_\pm(-x)) \quad (4a)$$

The set of parameters K_+ and K_- are controlled by the interaction term $\frac{g_2'' - g_1''}{2\pi V_\pm}$. As a result the hamiltonian in eq. 3 takes the form:

$$\begin{aligned} H^{(1)} = & \int_{-L}^L dx \left\{ \pi \tilde{V}_+ \tilde{J}_+^2(x) + \pi \tilde{V}_- \tilde{J}_-^2(x) \right. \\ & + \left[g_2^\perp (b^2 - a^2) \frac{1}{2} \left(\left(\frac{K_+}{K_-} \right)^{\frac{1}{2}} + \left(\frac{K_+}{K_-} \right)^{-\frac{1}{2}} \right) \right. \\ & \quad \left. + \left(g_4 (b^2 - a^2) + 2\pi ab (V_\uparrow - V_\downarrow) \right) \frac{1}{2} \left(\frac{K_+}{K_-} \right)^{\frac{1}{2}} - \left(\frac{K_+}{K_-} \right)^{-\frac{1}{2}} \right] \tilde{J}_+(x) \tilde{J}_-(-x) \\ & + \left[g_2^\perp (b^2 - a^2) \frac{1}{2} \left(\left(\frac{K_+}{K_-} \right)^{\frac{1}{2}} - \left(\frac{K_+}{K_-} \right)^{-\frac{1}{2}} \right) \right. \\ & \quad \left. + \left(g_4 (b^2 - a^2) + 2\pi ab (V_\uparrow - V_\downarrow) \right) \frac{1}{2} \left(\frac{K_+}{K_-} \right)^{\frac{1}{2}} + \left(\frac{K_+}{K_-} \right)^{-\frac{1}{2}} \right] \tilde{J}_+(x) \tilde{J}_-(x) \left. \right\} \end{aligned} \quad (5a)$$

In eq. 5a the renormalized velocities $\tilde{V}_\pm$, $V_\pm$ and interaction parameters $K_\pm$ are given by:

$$\begin{aligned} V_+ &= V_\uparrow a^2 + V_\downarrow b^2 + \frac{g_4}{\pi} ab \\ V_- &= V_\downarrow a^2 + V_\uparrow b^2 - \frac{g_4}{\pi} ab \end{aligned} \quad (5b)$$

The effect of the transformation in eq. 4a is to replace $V_\uparrow, V_\downarrow$ by $V_\pm$. The transformation in eq. 4b replaces $V_\pm$ by $\tilde{V}_\pm$, $\tilde{V}_\pm = \frac{V_\pm}{(K_\pm + K_\pm^{-1})/2}$. The interaction parameters defined in eq. 4b take the values such that the first term in eq 3b has been eliminated.

$$K_\pm = \sqrt{\frac{1 - R_\pm}{1 + R_\pm}}, \quad R_\pm = \frac{g_2'' - g_1''}{2\pi V_\pm} \quad (5c)$$

Using $V_\uparrow = V_F + \frac{\Delta}{2}$, $V_\downarrow = V_F - \frac{\Delta}{2}$, $\Delta > 0$ we observe from eq. 5c that for $g_2'' - g_1'' > 0$, $K_+ > K_-$. We will show tat due to the anisotropy in the $K_\pm$ variables the wire will be

polarized. In eq. 5a we will choose the coefficient of $\tilde{J}_+(x)\tilde{J}_-(-x)$ to vanish. As a result we will determine the parameters a and b , $a^2 + b^2 = 1$.

$$a = \frac{1}{\sqrt{2}} \left[1 + \sqrt{\frac{1}{1 + (g_2^\perp I + g_4)/\pi\Delta}} \right]^{1/2} \quad (5d)$$

where

$$I = \frac{1 + K_-/K_+}{1 - K_-/K_+} \quad (5e)$$

For large Δ we introduce the parameter $\eta \equiv \frac{g_2^\perp I + g_4}{2\pi\Delta} < 1$ and find $a \simeq 1 - \eta^2$, $b \simeq \eta^2$. Once the coefficients a and b are determined eq.5a takes the form:

$$H^{(1)} = \int_{-L}^L dx \left\{ \pi \tilde{V}_+ \tilde{J}_+^2(x) + \pi \tilde{V}_- \tilde{J}_-^2(x) + 4g_2^\perp (a^2 - b^2) \frac{\sqrt{K_+ K_-}}{K_+ - K_-} \tilde{J}_+(x) \tilde{J}_-(x) \right\} \quad (6a)$$

The mixed term $\tilde{J}_+(x)\tilde{J}_-(x)$ is removed by the linear transformation:

$$\begin{aligned} \tilde{J}_+(x) &= \alpha \tilde{J}_\uparrow(x) + \beta \tilde{J}_\downarrow(x) \\ \tilde{J}_-(x) &= \beta \tilde{J}_\uparrow(x) + \alpha \tilde{J}_\downarrow(x), \quad \alpha^2 + \beta^2 = 1 \end{aligned} \quad (6b)$$

We substitute eq. 6b into eq. 6a and obtain:

$$H^{(1)} = \int_{-L}^L dx \left\{ \pi \tilde{V}_\uparrow \tilde{J}_\uparrow^2(x) + \pi \tilde{V}_\downarrow \tilde{J}_\downarrow^2(x) \right\} \quad (6c)$$

where

$$\begin{aligned} \tilde{V}_\uparrow &= \alpha^2 \tilde{V}_+ + \beta^2 \tilde{V}_- + \frac{4\alpha\beta}{\pi} g_2^\perp (a^2 - b^2) \\ \tilde{V}_\downarrow &= \alpha^2 \tilde{V}_- + \beta^2 \tilde{V}_+ - \frac{4\alpha\beta}{\pi} g_2^\perp (a^2 - b^2) \end{aligned} \quad (6d)$$

The values of α, β are obtained by the requirement that the coefficient of $\tilde{J}_\uparrow(x)\tilde{J}_\downarrow(x)$ vanishes.

$$4(a^2 - b^2)(\beta^2 - \alpha^2)g_2^\perp \frac{\sqrt{K_+ K_-}}{K_+ - K_-} + 2\pi\alpha\beta(\tilde{V}_+ - \tilde{V}_-) = 0 \quad (6e)$$

with the solution,

$$\alpha = \frac{1}{\sqrt{2}} \left[1 + \frac{1}{\sqrt{1 + \varepsilon^2}} \right]^{1/2}, \quad \varepsilon \equiv \frac{2g_2^\perp (a + b^2)}{\pi\tilde{\Delta}} \frac{\sqrt{K_+ K_-}}{K_+ - K_-} \quad (6f)$$

where $\tilde{\Delta} = \tilde{V}_+ - \tilde{V}_-$. Again for $\varepsilon < 1$ we obtain $\alpha \approx 1 - (\frac{\varepsilon}{2})^2$, $\beta \approx (\frac{\varepsilon}{2})^2$. The set of transformation 4a, 4b 6b give the following relation between the “free” bosons $\theta_\uparrow(x)$, $\theta_\downarrow(x)$ and the interacting one $\tilde{\theta}_\uparrow(x)$, $\tilde{\theta}_\downarrow(x)$.

$$\begin{aligned} \theta_\uparrow(x) = & (\tilde{\theta}_\uparrow(x) - \tilde{\theta}_\uparrow(-x))(a\alpha K_+^{1/2} + b\beta K_-^{1/2})\frac{1}{2} + (\tilde{\theta}_\downarrow(x) - \tilde{\theta}_\downarrow(-x))(a\beta K_+^{1/2} - b\alpha K_-^{1/2})\frac{1}{2} \\ & + (\tilde{\theta}_\uparrow(x) + \tilde{\theta}_\uparrow(-x))(a\alpha K_+^{-1/2} - b\beta K_-^{-1/2})\frac{1}{2} + (\tilde{\theta}_\downarrow(x) + \tilde{\theta}_\downarrow(-x))(a\beta K_+^{-1/2} - b\alpha K_-^{-1/2})\frac{1}{2} \end{aligned} \quad (7a)$$

and similarly $\theta_\downarrow(x)$ is obtained from $\theta_\uparrow(x)$ by replacing $K_+ \rightarrow K_-$, $K_- \rightarrow K_+$. In the limit that the “flip” interaction parameters g_4 and $g_2^\perp$ are smaller than the Zeeman interaction Δ , we replace $a \sim 1 - \eta^2$, $b \sim \eta^2$, $\alpha \simeq 1$, $\beta \simeq 0$ and find for $\eta < 1$,

$$\begin{aligned} \theta_\uparrow(x) \approx & \frac{1}{2}(\tilde{\theta}_\uparrow(x) - \tilde{\theta}_\uparrow(-x))aK_+^{1/2} + \frac{1}{2}(\tilde{\theta}_\uparrow(x) + \tilde{\theta}_\uparrow(-x))aK_+^{-1/2} \\ & - \frac{1}{2}(\tilde{\theta}_\downarrow(x) - \tilde{\theta}_\downarrow(-x))bK_-^{1/2} - \frac{1}{2}(\tilde{\theta}_\downarrow(x) + \tilde{\theta}_\downarrow(-x))bK_-^{-1/2} \end{aligned} \quad (7b)$$

From eq. 7a we observe that the “spin flip” contribution is reduced by a factor $b/a \sim \eta^2$.

Next we consider a metallic wire confined in the region $0 \leq x \leq L$, for which we use again open boundary conditions. We bosonize the metallic hamiltonian using a periodic fermion field $\Phi_\sigma(x) = \frac{1}{\sqrt{2\pi a}} \exp[i\sqrt{4\pi}\varphi_\sigma(x)]$, where $\varphi_\sigma(x)$ is a chiral boson. The hamiltonian for the metal is given by,

$$H^{(2)} = \int_{-L}^L dx \left\{ V_F(\partial_x \varphi_\uparrow)^2 + V_F(\partial_x \varphi_\downarrow)^2 \right\} \quad (8)$$

In order to study tunnelling between the metal and the polarized wire we consider the following tunnelling hamiltonian:

$$H_T = t \left[\psi_\uparrow^+ \left(-\frac{d}{2} \right) \Phi_\uparrow^+ \left(\frac{d}{2} \right) + \psi_\downarrow^+ \left(-\frac{d}{2} \right) \Phi_\downarrow^+ \left(\frac{d}{2} \right) + h.c. \right] \quad (9)$$

Using eq. 7a we find for H_T the representation:

$$\begin{aligned} H_T \approx & \frac{t}{\pi d} \left[\cos \sqrt{4\pi} (\tilde{\theta}_\uparrow(0)\gamma_{\uparrow\uparrow}^{1/2} + \tilde{\theta}_\downarrow(0)\gamma_{\uparrow\downarrow}^{1/2} - \varphi_\uparrow(0)) \right. \\ & \left. + \cos \sqrt{4\pi} (\tilde{\theta}_\downarrow(0)\gamma_{\downarrow\downarrow}^{1/2} + \tilde{\theta}_\uparrow(0)\gamma_{\downarrow\uparrow}^{1/2} - \varphi_\downarrow(0)) \right]; \quad d \ll L \end{aligned} \quad (10)$$

In eq. 10 we have ignored the “d” dependence in the cosine term. The parameters $\gamma_{\uparrow\uparrow}$, $\gamma_{\downarrow\downarrow}$, $\gamma_{\uparrow\downarrow}$, $\gamma_{\downarrow\uparrow}$ are given by

$$\begin{aligned} \gamma_{\uparrow\uparrow}^{1/2} &= a\alpha K_+^{-1/2} + b\beta K_-^{-1/2}, & \gamma_{\uparrow\downarrow}^{1/2} &= a\beta K_+^{-1/2} - b\alpha K_+^{1/2}, \\ \gamma_{\downarrow\downarrow}^{1/2} &= b\beta K_+^{-1/2} + a\alpha K_-^{-1/2}, & \gamma_{\downarrow\uparrow}^{1/2} &= b\alpha K_+^{-1/2} + a\beta K_-^{-1/2}. \end{aligned} \quad (11)$$

We consider the hamiltonian $H = H^{(1)} + H^{(2)} + H_T$ in the diagonal form given by $H^{(1)}$ in eq. 6c, and $H^{(2)}$ by eq. 8 and the tunnelling term H_T given by eq. 10. The effect of tunnelling term H_T is investigated within the Renormalization Group (R.G.). Performing a differential R.G. $\Lambda \rightarrow \Lambda' = \Lambda - d\Lambda = \Lambda e^{-s}$, $s > 0$, we find from the scaling dimensions of the field $\tilde{\theta}_\uparrow$, $\tilde{\theta}_\downarrow$, $\varphi_\uparrow$, $\varphi_\downarrow$, that the tunnelling matrix elements $t^\uparrow = t$ and $t^\downarrow = t$ obey the following scaling equations:

$$\frac{dt^\uparrow}{ds} = t^\uparrow \left[1 - \frac{1}{2}(1 + \gamma_{\uparrow,\uparrow} + \gamma_{\uparrow,\downarrow}) \right] \approx \frac{1}{2} t^\uparrow \left[1 - \frac{a^2}{K_+} - \frac{b^2}{K_-} \right] \quad (12a)$$

$$\frac{dt^\downarrow}{ds} = t^\downarrow \left[1 - \frac{1}{2}(1 + \gamma_{\downarrow,\downarrow} + \gamma_{\downarrow,\uparrow}) \right] \approx \frac{1}{2} t^\downarrow \left[1 - \frac{a^2}{K_-} - \frac{b^2}{K_+} \right] \quad (12b)$$

We solved eqs. 10a, 10b in terms of the length scale $e^s \equiv \ell = \frac{1}{a} \min[L, L_T]$, we find:

$$G_\uparrow \simeq \frac{e^2}{h} |t|^2 \ell^{\left(\frac{a^2}{K_+} + \frac{b^2}{K_-} - 1\right)} \quad (13a)$$

$$G_\downarrow \simeq \frac{e^2}{h} |t|^2 \ell^{\left(\frac{a^2}{K_-} + \frac{b^2}{K_+} - 1\right)} \quad (13b)$$

The parameter K_+ , K_- , a^2 and b^2 are given by equation 5c and 5d. They obey the conditions $1 \geq K_+ \gg K_-$ and $a^2 \gg b^2$, $a^2 + b^2 = 1$. We introduce the notations, $\frac{a^2}{K_+} + \frac{b^2}{K_-} - 1 \equiv 2(\frac{1}{K_\uparrow} - 1)$, $\frac{a^2}{K_-} + \frac{b^2}{K_+} - 1 \equiv 2(\frac{1}{K_\downarrow} - 1)$ and find the conductance $G_\uparrow$ and $G_\downarrow$ in terms of the Luttinger exponents, $K_\uparrow$, $K_\downarrow$. From equation 5c we observe that for repulsion interactions the anisotropy in the velocities $V_\uparrow > V_\downarrow$ causes the anisotropy in the $K_\pm$ values, $1 > K_+ > K_- > 0$ and therefore $1 > K_\uparrow > K_\downarrow > 0$. For large Zeeman splitting $\Delta = V_\uparrow - V_\downarrow$ we find $K_\uparrow \gg K_\downarrow$ and therefore a strong anisotropy in the conductance G is obtained, $G_\uparrow \gg G_\downarrow$. The ratio between the two conductances, $r \equiv G_\downarrow/G_\uparrow$ allows to define the polarization degree P .

$$P = \frac{G_\uparrow - G_\downarrow}{G_\uparrow + G_\downarrow} \approx \frac{1 - r}{1 + r} \quad (14a)$$

For long wires L at temperature T which obey $L > L_T$ the infrared cutoff is provided by the thermal length and therefore we find, $r \equiv \left(\frac{T}{T_F}\right)^{2\left(\frac{K_\uparrow - K_\downarrow}{K_\uparrow K_\downarrow}\right)}$ where

$$2\frac{K_\uparrow - K_\downarrow}{K_\uparrow K_\downarrow} = \left(\frac{g_2'' - g_1''}{2\pi V_F}\right) \left(\frac{\Delta}{V_F}\right) \left(\frac{1}{1 - \left(\frac{\Delta}{2V_F}\right)^2}\right) > 0 \quad (14b)$$

From eq. 14 we observe that the polarization degree is enhanced at low temperatures with the increase of the Zeeman term Δ .

The interaction term $g_2'' - g_1''$ controls the polarization. From eq. 3b we observe that the Luttinger parameter which controls separately the spin up and spin down excitations is given by $g_2'' - g_1''$. For a Hubbard model (7) $g_2'' = g_1''$ and we have no effect! In order to obtain $g_2'' - g_1'' \neq 0$ we need an extended Hubbard model with large momentum transfer. The situation is similar to a Kondo problem where we have two Kondo parameters - $J_{\parallel}$ and $J_{\perp}$. For attractive interactive interactions a spin gap is caused by a negative $g_1^{\perp}$. For $\Delta \neq 0$ the gap is avoided by the oscillating term $2K_F(\frac{\Delta}{2V_F})x$ which appears in the “cosine” term (the last term in eq. 3b). [More precisely we can argue that g_1 becomes more negative under scaling. The growth of $|g_1|$ is stopped at the length scale $(\exp \ell^*)2K_F(\frac{\Delta}{2V_F})d \simeq \pi$ (“d” is the lattice spacing). Therefore for the length scale $\ell > \ell^*$ we can safely drop the “cosine” term in eq. 3b.]

In order to estimate the polarization at finite temperature produced by the anisotropic tunnelling, $K_{\uparrow} \neq K_{\downarrow}$ we use the results given by eqs. 11, 12. Using typical values of $\frac{T}{T_F} \simeq 10^{-3} > \frac{a}{L}$, $\frac{\Delta}{2V_F} \simeq 0.5$ and $\frac{g_2'' - g_1''}{2\pi V_F} \simeq 0.5$, we obtain a polarization degree $P \simeq 80\%$. Here we have investigated the case where the Zeeman splitting is large, as a result we obtain two Luttinger liquids for spin up and spin down. In the opposite limit $\Delta \rightarrow 0$ we obtain two Luttinger liquids for spin and charge excitations. The tunnelling conductance will depend only on one exponent $K_c = K_{\uparrow} = K_{\downarrow}$, the charge exponent (see ref. 5), but not separately on $K_{\uparrow}$ and $K_{\downarrow}$.

To conclude the possibility for a magnetic wire and the simulation of the F.M.-M.-F.M., transistor is suggested. The idea is based on the fact that the Luttinger interaction parameter $K_{\uparrow} \neq K_{\downarrow}$. As a result at the interface between two systems one polarization will be reflected and only the second polarization is able to tunnel into the second wire.

-
- [1] A. G. Aronov, JETP. Lett. **24**, 33 (1976).
 - [2] R. Fiederling, M. Klein, W. Ossau, G. Schmidt, A. Waag, and L. W. Molenkamp, Nature **402**, 787 (1999); T. Dietl, H. Ohno, F. Matsukura, J. Cibert, and D. Ferrand, Science **287**, 1019 (2000).
 - [3] S. Datta, and B. Das, Applied Phys. Lett. **56**, 12 (1990).
 - [4] A. Bratos, Yu V. Nazarov, J. Inoue, and G. Bauer, Phys. Rev. B **59**, 93 (1999).

- [5] C. L. Kane, and M.P.A. Fisher, Phys. Rev. Lett. **68**, 1220 (1991); A. Yacoby, H. L. Stormer, N. S. Wingreen, L. N. Pfeiffer, K. W. Baldwin ,and R. W. West , Phys. Rev. Lett. **77**, 4612 (1996).
- [6] A. Gogolin, A. Nersesyan, and A. Tsvelik, “Bosonization and Strongly Correlated Systems”, Cambridge University Press (1998).
- [7] A. Luther, and V. J. Emery, Phys. Rev. Lett. **33**, 589 (1974).